

# LM75A

## Digital Temperature Sensor and Thermal Watchdog with Two-Wire Interface

### General Description

The LM75A is an industry-standard digital temperature sensor with an integrated Sigma-Delta analog-to-digital converter and I<sup>2</sup>C® interface. The LM75A provides 9-bit digital temperature readings with an accuracy of  $\pm 2^{\circ}\text{C}$  from  $-25^{\circ}\text{C}$  to  $100^{\circ}\text{C}$  and  $\pm 3^{\circ}\text{C}$  over  $-55^{\circ}\text{C}$  to  $125^{\circ}\text{C}$ .

The LM75A operates with a single supply from +2.7V to +5.5V. Communication is accomplished over a 2-wire interface which operates up to 400kHz. The LM75A has three address pins, allowing up to eight LM75A devices to operate on the same 2-wire bus. The LM75A has a dedicated over-temperature output (O.S.) with programmable limit and hysteresis. This output has programmable fault tolerance, which allows the user to define the number of consecutive error conditions that must occur before O.S. is activated.

The wide temperature and supply range and I<sup>2</sup>C interface make the LM75A ideal for a number of applications including base stations, electronic test equipment, office electronics, personal computers, and any other system where thermal management is critical to performance. The LM75A is available in an SOP-8 package and an MSOP-8 package.

### Applications

- General System Thermal Management
- Communications Infrastructure
- Electronic Test Equipment
- Environmental Monitoring


### Features

- No external components required
- Shutdown mode to minimize power consumption
- Up to eight LM75As can be connected to a single bus
- Power up defaults permit stand-alone operation as thermostat

### Key Specifications

|                        |  |                               |
|------------------------|--|-------------------------------|
| ■ Supply Voltage       | LM75A  | 2.7V to 5.5V                  |
| ■ Supply Current       | operating                                      | 280 $\mu\text{A}$ (typ)       |
|                        | shutdown                                       | 4 $\mu\text{A}$ (typ)         |
| ■ Temperature Accuracy | $-25^{\circ}\text{C}$ to $100^{\circ}\text{C}$ | $\pm 2^{\circ}\text{C}$ (max) |
|                        | $-55^{\circ}\text{C}$ to $125^{\circ}\text{C}$ | $\pm 3^{\circ}\text{C}$ (max) |


### Simplified Block Diagram



1265819

# Connection Diagram

LM75A SOP-8 and MSOP-8




1265802

## Pin Descriptions

| Label           | Pin # | Function   | Typical Connection  |
|-----------------|-------|--|---|
| SDA             | 1     | I <sup>2</sup> C Serial Bi-Directional Data Line, Open Drain | From Controller, tied to a pull-up resistor or current source   |
| SCL             | 2     | I <sup>2</sup> C Clock Input                                 | From Controller, tied to a pull-up resistor or current source   |
| O.S.            | 3     | Overtemperature Shutdown, Open Drain Output                  | Pull-up Resistor, Controller Interrupt Line   |
| GND             | 4     | Power Supply Ground  | Ground  |
| +V <sub>S</sub> | 8     | Positive Supply Voltage Input                                | DC Voltage from 2.7V to 5.5V 100 nF bypass capacitor with 10 μF bulk capacitance in the near vicinity |
| A0–A2           | 7,6,5 | User-Set I <sup>2</sup> C Address Inputs                     | Ground (Low, “0”) or +V <sub>S</sub> (High, “1”)  |

## Typical Application



1265803

FIGURE 1. Typical Application

## Ordering Information

| Order Number | Package Marking | NS Package Number  | Supply Voltage | Transport Media             | Noise Filter on SDA and SCL |
|--------------|-----------------|--------------------|----------------|-----------------------------|-----------------------------|
| LM75AIM      | LM75AIM         | M08A<br>(SOP-8)    | 3.3V, 5V       | 95 units in Rail            | Yes                         |
| LM75AIMX     | LM75AIM         | M08A<br>(SOP-8)    | 3.3V, 5V       | 2500 units on Tape and Reel | Yes                         |
| LM75AIMM     | T00A            | MUA08A<br>(MSOP-8) | 3.3V, 5V       | 1000 units on Tape and Reel | Yes                         |
| LM75AIMMX    | T00A            | MUA08A<br>(MSOP-8) | 3.3V, 5V       | 3500 units on Tape and Reel | Yes                         |
| LM75AIMME    | T00A            | MUA08A<br>(MSOP-8) | 3.3V, 5V       | 250 units on Tape and Reel  | Yes                         |

## Absolute Maximum Ratings *(Note 1)*

|  |   |
|--|---|
| Supply Voltage Pin (+V <sub>S</sub> )    | -0.3V to 6.5V   |
| Voltage at A0, A1 and A2 Pins            | -0.3V to (+V <sub>S</sub> + 0.3V)<br>and must be ≤ 6.5V |
| Voltage at OS, SCL and SDA Pins          | -0.3V to 6.5V   |
| Input Current at any Pin <i>(Note 2)</i> | 5 mA  |
| Package Input Current <i>(Note 2)</i>    | 20 mA   |
| Storage Temperature                      | -65°C to +150°C   |
| ESD Susceptibility <i>(Note 4)</i>       | LM75A   |
| Human Body Model                         | 2500V   |
| Machine Model                            | 250V  |
| Charged Device Model                     | 1000V   |
| O.S. Output Sink Current                 | 10 mA   |
| O.S. Output Voltage                      | 6.5V  |

## Operating Ratings

|  |   |
|--|---|
| Specified Temperature Range<br><i>(Note 5)</i>   | T <sub>MIN</sub> to T <sub>MAX</sub><br>-55°C to +125°C |
| Supply Voltage Range (+V <sub>S</sub> )<br>LM75A   | +2.7V to +5.5V  |
| <i>Soldering process must comply with National Semiconductor's Reflow Temperature Profile specifications. Refer to <a href="http://www.national.com/packaging">www.national.com/packaging</a>. <i>(Note 3)</i></i> |   |

## Temperature-to-Digital Converter Characteristics

Unless otherwise noted, these specifications apply for: +V<sub>S</sub> = +2.7 to 5.5 Vdc for LM75AIM. **Boldface limits apply for T<sub>A</sub> = T<sub>J</sub> = T<sub>MIN</sub> to T<sub>MAX</sub>**; all other limits T<sub>A</sub> = T<sub>J</sub> = +25°C, unless otherwise noted.

| Parameter                             | Conditions                       | Typical<br><i>(Note 11)</i>         | Limits<br><i>(Note 6)</i> | Units<br><b>(Limit)</b> |          |
|---------------------------------------|----------------------------------|-------------------------------------|---------------------------|-------------------------|----------|
| Accuracy                              | T <sub>A</sub> = -25°C to +100°C |                                     | <b>±2.0</b>               | °C (max)                |          |
|                                       | T <sub>A</sub> = -55°C to +125°C |                                     | <b>±3.0</b>               |                         |          |
| Resolution                            |                                  | 9                                   |                           | Bits                    |          |
| Temperature Conversion Time           | <i>(Note 7)</i>                  | 100                                 | <b>300</b>                | ms (max)                |          |
| Quiescent Current                     | LM75A                            | I <sup>2</sup> C Inactive           | 0.28                      | <b>0.5</b>              | mA (max) |
|                                       |                                  | Shutdown Mode, +V <sub>S</sub> = 3V | 4                         |                         | μA       |
|                                       |                                  | Shutdown Mode, +V <sub>S</sub> = 5V | 6                         |                         | μA       |
| O.S. Output Saturation Voltage        | I <sub>OUT</sub> = 4.0 mA        |                                     | <b>0.8</b>                | V (max)                 |          |
| O.S. Delay                            | <i>(Note 9)</i>                  |                                     | <b>1</b>                  | Conversion (min)        |          |
|                                       |                                  |                                     | <b>6</b>                  | Conversions (max)       |          |
| T <sub>OS</sub> Default Temperature   | <i>(Note 10)</i>                 | 80                                  |                           | °C                      |          |
| T <sub>HYST</sub> Default Temperature | <i>(Note 10)</i>                 | 75                                  |                           | °C                      |          |

## Logic Electrical Characteristics

### DIGITAL DC CHARACTERISTICS


Unless otherwise noted, these specifications apply for  $+V_S = +2.7$  to  $5.5$  Vdc for LM75AIM and LM75AIMM. **Boldface limits apply for  $T_A = T_J = T_{MIN}$  to  $T_{MAX}$** ; all other limits  $T_A = T_J = +25^\circ\text{C}$ , unless otherwise noted.

| Symbol      | Parameter                                       |       | Conditions                                   | Typical<br>(Note 11) | Limits<br>(Note 6) | Units<br>(Limit)    |
|-------------|---|-------|--|----------------------|--------------------|---------------------|
| $V_{IN(1)}$ | Logical "1" Input Voltage                       |       |  |                      | $+V_S \times 0.7$  | V (min)             |
|             |   |       |  |                      | $+V_S + 0.3$       | V (max)             |
| $V_{IN(0)}$ | Logical "0" Input Voltage                       |       |  |                      | $-0.3$             | V (min)             |
|             |   |       |  |                      | $+V_S \times 0.3$  | V (max)             |
| $I_{IN(1)}$ | Logical "1" Input Current                       |       | $V_{IN} = +V_S$                              | 0.005                | <b>1.0</b>         | $\mu\text{A}$ (max) |
| $I_{IN(0)}$ | Logical "0" Input Current                       |       | $V_{IN} = 0\text{V}$                         | -0.005               | <b>-1.0</b>        | $\mu\text{A}$ (max) |
| $C_{IN}$    | All Digital Inputs                              |       |  | 5                    |                    | pF                  |
| $I_{OH}$    | High Level Output Current<br>Open drain leakage | LM75A | $V_{OH} = 5\text{V}$                         |                      | <b>1</b>           | $\mu\text{A}$ (max) |
| $V_{OL}$    | Low Level Output Voltage                        |       | $I_{OL} = 3\text{ mA}$                       |                      | <b>0.4</b>         | V (max)             |
| $t_{OF}$    | Output Fall Time                                |       | $C_L = 400\text{ pF}$<br>$I_O = 3\text{ mA}$ |                      | <b>250</b>         | ns (max)            |

### I<sup>2</sup>C DIGITAL SWITCHING CHARACTERISTICS

Unless otherwise noted, these specifications apply for  $+V_S = +2.7$  to  $5.5$  Vdc for LM75AIM and LM75AIMM on output lines =  $80\text{ pF}$  unless otherwise specified. **Boldface limits apply for  $T_A = T_J = T_{MIN}$  to  $T_{MAX}$** ; all other limits  $T_A = T_J = +25^\circ\text{C}$ , unless otherwise noted.

| Symbol        | Parameter  |       | Conditions | Typical<br>(Note 11) | Limits<br>(Note 6,<br>Note 13) | Units<br>(Limit)    |
|---------------|--|-------|------------|----------------------|--------------------------------|---------------------|
| $t_1$         | SCL (Clock) Period                                   |       |            |                      | <b>2.5</b>                     | $\mu\text{s}$ (min) |
| $t_2$         | Data in Set-Up Time to SCL High                      |       |            |                      | <b>100</b>                     | ns (min)            |
| $t_3$         | Data Out Stable after SCL Low                        |       |            |                      | <b>0</b>                       | ns (min)            |
| $t_4$         | SDA Low Set-Up Time to SCL Low (Start Condition)     |       |            |                      | <b>100</b>                     | ns (min)            |
| $t_5$         | SDA High Hold Time after SCL High (Stop Condition)   |       |            |                      | <b>100</b>                     | ns (min)            |
| $t_{TIMEOUT}$ | SDA Time Low for Reset of Serial Interface (Note 12) | LM75A |            |                      | <b>75</b>                      | ms (min)            |
|               |  |       |            |                      | <b>325</b>                     | ms (max)            |



1265804

**Note 1:** Absolute Maximum Ratings indicate limits beyond which damage to the device may occur. DC and AC electrical specifications do not apply when operating the device beyond its rated operating conditions.

**Note 2:** When the input voltage ( $V_I$ ) at any pin exceeds the power supplies ( $V_I < GND$  or  $V_I > +V_S$ ) the current at that pin should be limited to 5mA. The 20mA maximum package input current rating limits the number of pins that can safely exceed the power supplies with an input current of 5mA to four.

**Note 3:** Reflow temperature profiles are different for lead-free and non-lead-free packages.

**Note 4:** Human body model, 100pF discharged through a 1.5k $\Omega$  resistor. Machine model, 200pF discharged directly into each pin. The Charged Device Model (CDM) is a specified circuit characterizing an ESD event that occurs when a device acquires charge through some triboelectric (frictional) or electrostatic induction processes and then abruptly touches a grounded object or surface.

**Note 5:** LM75A  $\theta_{JA}$  (thermal resistance, junction-to-ambient) when attached to a printed circuit board with 2oz. foil similar to the one shown in [Figure 3](#) is summarized in the table below:

| Device Number | NS Package Number | Thermal Resistance ( $\theta_{JA}$ ) |
|---------------|-------------------|--------------------------------------|
| LM75AIM       | M08A              | 200°C/W                              |
| LM75AIMM      | MUA08A            | 250°C/W                              |

**Note 6:** Limits are guaranteed to National's AOQL (Average Outgoing Quality Level).

**Note 7:** The conversion-time specification is provided to indicate how often the temperature data is updated. The LM75A can be accessed at any time and reading the Temperature Register will yield result from the last temperature conversion. When the LM75A is accessed, the conversion that is in process will be interrupted and it will be restarted after the end of the communication. Accessing the LM75A continuously without waiting at least one conversion time between communications will prevent the device from updating the Temperature Register with a new temperature conversion result. Consequently, the LM75A should not be accessed continuously with a wait time of less than 300ms.

**Note 8:** For best accuracy, minimize output loading. Higher sink currents can affect sensor accuracy with internal heating. This can cause an error of 0.64°C at full rated sink current and saturation voltage based on junction-to-ambient thermal resistance.


**Note 9:** O.S. Delay is user programmable up to 6 "over limit" conversions before O.S. is set to minimize false tripping in noisy environments.

**Note 10:** Default values set at power up.

**Note 11:** Typicals are at  $T_A = 25^\circ\text{C}$  and represent most likely parametric norm.


**Note 12:** Holding the SDA line low for a time greater than  $t_{\text{TIMEOUT}}$  will cause the LM75A to reset SDA to the IDLE state of the serial bus communication (SDA set High).

**Note 13:** Timing specifications are tested at the bus input logic levels ( $V_{in(0)}=0.3XVA$  for a falling edge and  $V_{in(1)}=0.7XVA$  for a rising edge) when the SCL and SDA edge rates are similar.



1265805


FIGURE 2. Temperature-to-Digital Transfer Function (Non-linear scale for clarity)



1265806

FIGURE 3. Printed Circuit Board Used for Thermal Resistance Specifications

## Typical Performance Characteristics



### 1.0 Functional Description

The LM75A temperature sensor incorporates a band-gap type temperature sensor and 9-bit ADC (Sigma-Delta Analog-to-Digital Converter). The temperature data output of the LM75A is available at all times via the I<sup>2</sup>C bus. If a conversion is in progress, it will be stopped and restarted after the read. A digital comparator is also incorporated that compares a series of readings, the number of which is user-selectable, to user-programmable setpoint and hysteresis values. The comparator trips the O.S. output line, which is programmable for mode and polarity. The LM75A has an integrated low-pass filter on both the SDA and the SCL line. These filters increase communications reliability in noisy environments.

The LM75A also has a bus fault timeout feature. If the SDA line is held low for longer than  $t_{\text{TIMEOUT}}$  (see specification) the LM75A will reset to the IDLE state (SDA set to high impedance) and wait for a new start condition. The TIMEOUT feature is not functional in Shutdown Mode.

#### 1.1 O.S. OUTPUT, $T_{\text{OS}}$ AND $T_{\text{HYST}}$ LIMITS

In Comparator mode the O.S. Output behaves like a thermostat. The output becomes active when temperature exceeds the  $T_{\text{OS}}$  limit, and leaves the active state when the temperature drops below the  $T_{\text{HYST}}$  limit. In this mode the O.S. output can be used to turn a cooling fan on, initiate an emergency system shutdown, or reduce system clock speed. Shutdown mode does not reset O.S. state in a comparator mode.

In Interrupt mode exceeding  $T_{\text{OS}}$  also makes O.S. active but O.S. will remain active indefinitely until reset by reading any register via the I<sup>2</sup>C interface. Once O.S. has been activated by crossing  $T_{\text{OS}}$ , then reset, it can be activated again only by Temperature going below  $T_{\text{HYST}}$ . Again, it will remain active indefinitely until being reset by a read. Placing the LM75A in shutdown mode also resets the O.S. Output.

#### 1.2 POWER UP AND POWER DOWN

The LM75A always powers up in a known state. The power up default conditions are:

1. Comparator mode
2.  $T_{\text{OS}} = 80^{\circ}\text{C}$
3.  $T_{\text{HYST}} = 75^{\circ}\text{C}$
4. O.S. active low
5. Pointer = "00"

When the supply voltage is less than about 1.7V, the LM75A is considered powered down. As the supply voltage rises above the nominal 1.7V power up threshold, the internal registers are reset to the power up default values listed above.

#### 1.2.1 Stand-Alone Thermostat Mode


If the LM75A is *not connected* to the I<sup>2</sup>C bus on power up, it will act as a stand-alone thermostat with the power up default conditions listed above. It is optional, but recommended, to connect the address pins (A2, A1, A0) and the SCL and SDA pins together and to a 10k pull-up resistor to  $+V_{\text{S}}$  for better noise immunity. Any of these pins may also be tied high separately through a 10k pull-up resistor.

#### 1.3 I<sup>2</sup>C BUS INTERFACE

The LM75A operates as a slave on the I<sup>2</sup>C bus, so the SCL line is an input (no clock is generated by the LM75A) and the SDA line is a bi-directional serial data path. According to I<sup>2</sup>C bus specifications, the LM75A has a 7-bit slave address. The four most significant bits of the slave address are hard wired inside the LM75A and are "1001". The three least significant bits of the address are assigned to pins A2–A0, and are set by connecting these pins to ground for a low, (0); or to  $+V_{\text{S}}$  for a high, (1).

Therefore, the complete slave address is:

|     |   |   |   |     |    |    |
|-----|---|---|---|-----|----|----|
| 1   | 0 | 0 | 1 | A2  | A1 | A0 |
| MSB |   |   |   | LSB |    |    |



1265807

**Note 14:** These interrupt mode resets of O.S. occur only when LM75A is read or placed in shutdown. Otherwise, O.S. would remain active indefinitely for any event.

**FIGURE 4. O.S. Output Temperature Response Diagram**

### 1.4 TEMPERATURE DATA FORMAT

Temperature data can be read from the Temperature,  $T_{OS}$  Set Point, and  $T_{HYST}$  Set Point registers; and written to the  $T_{OS}$  Set Point, and  $T_{HYST}$  Set Point registers. Temperature data is represented by a 9-bit, two's complement word with an LSB (Least Significant Bit) equal to  $0.5^{\circ}\text{C}$ :

| Temperature | Digital Output |      |
|-------------|----------------|------|
|             | Binary         | Hex  |
| +125°C      | 0 1111 1010    | 0FAh |
| +25°C       | 0 0011 0010    | 032h |
| +0.5°C      | 0 0000 0001    | 001h |
| 0°C         | 0 0000 0000    | 000h |
| -0.5°C      | 1 1111 1111    | 1FFh |
| -25°C       | 1 1100 1110    | 1CEh |
| -55°C       | 1 1001 0010    | 192h |

### 1.5 SHUTDOWN MODE

Shutdown mode is enabled by setting the shutdown bit in the Configuration register via the I<sup>2</sup>C bus. Shutdown mode reduces power supply current significantly. See specified quiescent current specification in the electrical tables. In Interrupt mode O.S. is reset if previously set and is undefined in Comparator mode during shutdown. The I<sup>2</sup>C interface remains active. Activity on the clock and data lines of the I<sup>2</sup>C bus may slightly increase shutdown mode quiescent current.  $T_{OS}$ ,  $T_{HYST}$ , and Configuration registers can be read from and written to in shutdown mode.

For the LM75A, the TIMEOUT feature is turned off in Shutdown Mode.

### 1.6 FAULT QUEUE

A fault queue of up to 6 faults is provided to prevent false tripping of O.S. when the LM75A is used in noisy environments. The number of faults set in the queue must occur consecutively to set the O.S. output.

### 1.7 COMPARATOR/INTERRUPT MODE

As indicated in the O.S. Output Temperature Response Diagram, [Figure 4](#), the events that trigger O.S. are identical for either Comparator or Interrupt mode. The most important difference is that in Interrupt mode the O.S. will remain set indefinitely once it has been set. To reset O.S. while in Interrupt mode, perform a read from any register in the LM75A.

### 1.8 O.S. OUTPUT


The O.S. output is an open-drain output and does not have an internal pull-up. A “high” level will not be observed on this pin until pull-up current is provided from some external source, typically a pull-up resistor. Choice of resistor value depends on many system factors but, in general, the pull-up resistor should be as large as possible. This will minimize any errors due to internal heating of the LM75A. The maximum resistance of the pull up, based on LM75A specification for High Level Output Current, to provide a 2V high level, is 30kΩ.

### 1.9 O.S. POLARITY

The O.S. output can be programmed via the configuration register to be either active low (default mode), or active high. In active low mode the O.S. output goes low when triggered

exactly as shown on the O.S. Output Temperature Response Diagram, [Figure 4](#). Active high simply inverts the polarity of the O.S. output.

### 1.10 INTERNAL REGISTER STRUCTURE



1265820

There are four data registers in the LM75A and an additional Product ID register selected by the Pointer register. At power-up the Pointer is set to "000"; the location for the Temperature Register. The Pointer register latches whatever the last location it was set to. In Interrupt Mode, a read from the LM75A, or placing the device in shutdown mode, resets the O.S. output. All registers are read and write, except the Temperature register and the LM75A's Product ID register, which are read only.

A write to the LM75A will always include the address byte and the Pointer byte. A write to the Configuration register requires one data byte, and the  $T_{OS}$  and  $T_{HYST}$  registers require two data bytes.

Reading the LM75A can take place either of two ways: If the location latched in the Pointer is correct (most of the time it is expected that the Pointer will point to the Temperature regis-

ter because it will be the data most frequently read from the LM75A), then the read can simply consist of an address byte, followed by retrieving the corresponding number of data bytes. If the Pointer needs to be set, then an address byte, pointer byte, repeat start, and another address byte will accomplish a read.

The first data byte is the most significant byte with most significant bit first, permitting only as much data as necessary to be read to determine temperature condition. For instance, if the first four bits of the temperature data indicates an overtemperature condition, the host processor could immediately take action to remedy the excessive temperatures. At the end of a read, the LM75A can accept either Acknowledge or No Acknowledge from the Master (No Acknowledge is typically used as a signal for the slave that the Master has read its last byte).

**1.11 POINTER REGISTER (Selects which registers will be read from or written to):**

| P7 | P6 | P5 | P4 | P3 | P2              | P1 | P0 |
|----|----|----|----|----|-----------------|----|----|
| 0  | 0  | 0  | 0  | 0  | Register Select |    |    |

P0-P1: Register Select:

| P2 | P1 | P0 | Register                                   |
|----|----|----|--|
| 0  | 0  | 0  | Temperature (Read only) (Power-up default) |
| 0  | 0  | 1  | Configuration (Read/Write)                 |
| 0  | 1  | 0  | T <sub>HYST</sub> (Read/Write)             |
| 0  | 1  | 1  | T <sub>OS</sub> (Read/Write)               |
| 1  | 1  | 1  | Product ID Register                        |

P3-P7: Must be kept zero.

**1.12 TEMPERATURE REGISTER (Read Only):**

| D15 | D14   | D13   | D12   | D11   | D10   | D9    | D8    | D7  | D6 | D5 | D4 | D3 | D2 | D1 | D0 |
|-----|-------|-------|-------|-------|-------|-------|-------|-----|----|----|----|----|----|----|----|
| MSB | Bit 7 | Bit 6 | Bit 5 | Bit 4 | Bit 3 | Bit 2 | Bit 1 | LSB | X  | X  | X  | X  | X  | X  | X  |

D0-D6: Undefined. D7-D15: Temperature Data. One LSB = 0.5°C. Two's complement format.

**1.13 CONFIGURATION REGISTER (Read/Write):**

| D7 | D6 | D5 | D4          | D3 | D2            | D1      | D0       |
|----|----|----|-------------|----|---------------|---------|----------|
| 0  | 0  | 0  | Fault Queue |    | O.S. Polarity | Cmp/Int | Shutdown |

Power up default is with all bits "0" (zero).

D0: Shutdown: When set to 1 the LM75A goes to low power shutdown mode.

D1: Comparator/Interrupt mode: 0 is Comparator mode, 1 is Interrupt mode.

D2: O.S. Polarity: 0 is active low, 1 is active high. O.S. is an open-drain output under all conditions.

D3-D4: Fault Queue: Number of faults necessary to detect before setting O.S. output to avoid false tripping due to noise. Faults are determine at the end of a conversion. See specified temperature conversion time in the electrical tables.

| D4 | D3 | Number of Faults     |
|----|----|----------------------|
| 0  | 0  | 1 (Power-up default) |
| 0  | 1  | 2                    |
| 1  | 0  | 4                    |
| 1  | 1  | 6                    |

D5-D7: These bits are used for production testing and must be kept zero for normal operation.

**1.14 T<sub>HYST</sub> AND T<sub>OS</sub> REGISTER (Read/Write):**

| D15 | D14   | D13   | D12   | D11   | D10   | D9    | D8    | D7  | D6 | D5 | D4 | D3 | D2 | D1 | D0 |
|-----|-------|-------|-------|-------|-------|-------|-------|-----|----|----|----|----|----|----|----|
| MSB | Bit 7 | Bit 6 | Bit 5 | Bit 4 | Bit 3 | Bit 2 | Bit 1 | LSB | X  | X  | X  | X  | X  | X  | X  |

D0-D6: Undefined D7-D15: T<sub>HYST</sub> Or T<sub>OS</sub> Trip Temperature Data. Power up default is T<sub>OS</sub> = 80°C, T<sub>HYST</sub> = 75°C

**1.15 PRODID: PRODUCT ID REGISTER**


(Read Only) Pointer Address: 07h

| D7 | D6 | D5 | D4 | D3 | D2 | D1 | D0 |
|----|----|----|----|----|----|----|----|
| 1  | 0  | 1  | 0  | 0  | 0  | 0  | 1  |



D4--D7 Product Identification Nibble. Always returns Ah to uniquely identify this part as the LM75A.

D0--D3 Die Revision Nibble. Returns 1h to uniquely identify the revision level as one.


2.0 I<sup>2</sup>C Timing Diagrams



(a) Typical 2-Byte Read From Preset Pointer Location Such as Temp, T<sub>OS</sub>, T<sub>HYST</sub>




(b) Typical Pointer Set Followed by Immediate Read for 2-Byte Register such as Temp, T<sub>OS</sub>, T<sub>HYST</sub>




(c) Typical 1-Byte Read From Configuration Register With Preset Pointer


FIGURE 5. Timing Diagram



(a) Typical Pointer Set Followed by Immediate Read from Configuration Register



(b) Configuration Register Write



(c)  $T_{OS}$  and  $T_{HYST}$  Write

1265811

FIGURE 6. Timing Diagrams (Continued)

## 2.0 Application Hints

To get the expected results when measuring temperature with an integrated circuit temperature sensor like the LM75A, it is important to understand that the sensor measures its own die temperature. For the LM75A, the best thermal path between the die and the outside world is through the LM75A's pins. In the MSOP-8 package, the GND pin is directly connected to the die, so the GND pin provides the best thermal path. If the other pins are at different temperatures (unlikely, but possible), they will affect the die temperature, but not as strongly as the GND pin. In the SO-8 package, none of the pins is directly connected to the die, so they will all contribute similarly to the die temperature. Because the pins represent a good thermal path to the LM75A die, the LM75A will provide an accurate measurement of the temperature of the printed circuit board on which it is mounted. There is a less efficient thermal path between the plastic package and the LM75A die. If the ambient air temperature is significantly different from the printed circuit board temperature, it will have a small effect on the measured temperature.

In probe-type applications, the LM75A can be mounted inside a sealed-end metal tube, and can then be dipped into a bath or screwed into a threaded hole in a tank. As with any IC, the LM75A and accompanying wiring and circuits must be kept insulated and dry, to avoid leakage and corrosion. This is es-


pecially true if the circuit may operate at cold temperatures where condensation can occur. Printed-circuit coatings and varnishes such as Humiseal and epoxy paints or dips are often used to insure that moisture cannot corrode the LM75A or its connections.

### 2.1 DIGITAL NOISE ISSUES

The LM75A features an integrated low-pass filter on both the SCL and the SDA digital lines to mitigate the effects of bus noise. Although this filtering makes the LM75A communication robust in noisy environments, good layout practices are always recommended. Minimize noise coupling by keeping digital traces away from switching power supplies. Also, ensure that digital lines containing high-speed data communications cross at right angles to the SDA and SCL lines.

Excessive noise coupling into the SDA and SCL lines on the LM75A—specifically noise with amplitude greater than 400 mV<sub>pp</sub> (the LM75A's typical hysteresis), overshoot greater than 300mV above +V<sub>S</sub>, and undershoot more than 300 mV below GND—may prevent successful serial communication with the LM75A. Serial bus no-acknowledge is the most common symptom, causing unnecessary traffic on the bus. Although the serial bus maximum frequency of communication is only 400 kHz, care must be taken to ensure proper termination within a system with long printed circuit board traces or multiple parts on the bus.


## 3.0 Typical Applications



When using the two-wire interface: program O.S. for active high and connect O.S. directly to Q2's gate.


1265812

FIGURE 7. Simple Fan Controller, Interface Optional



1265821





FIGURE 8. Simple Thermostat, Interface Optional



1265822

FIGURE 9. Temperature Sensor with Loudmouth Alarm (Barking Watchdog)





**Physical Dimensions** inches (millimeters) unless otherwise noted



CONTROLLING DIMENSION IS MILLIMETER  
VALUES IN [ ] ARE INCHES  
DIMENSIONS IN ( ) FOR REFERENCE ONLY

M08A (Rev M)

**8-Lead (0.150 Wide) Molded Small Outline Package (SOP), JEDEC  
Order Number LM75AIM, LM75AIMX  
NS Package Number M08A**



CONTROLLING DIMENSION IS INCH  
VALUES IN [ ] ARE MILLIMETERS

MUA08A (Rev F)

**8-Lead (0.118 Wide) Molded Mini SOIC Wide Package  
Order Number LM75AIMM, LM75AIMMX  
NS Package Number MUA08A**

# Notes

**Notes**

## IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

TI products are not authorized for use in safety-critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, unless officers of the parties have executed an agreement specifically governing such use. Buyers represent that they have all necessary expertise in the safety and regulatory ramifications of their applications, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of TI products in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by TI. Further, Buyers must fully indemnify TI and its representatives against any damages arising out of the use of TI products in such safety-critical applications.

TI products are neither designed nor intended for use in military/aerospace applications or environments unless the TI products are specifically designated by TI as military-grade or "enhanced plastic." Only products designated by TI as military-grade meet military specifications. Buyers acknowledge and agree that any such use of TI products which TI has not designated as military-grade is solely at the Buyer's risk, and that they are solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI products are neither designed nor intended for use in automotive applications or environments unless the specific TI products are designated by TI as compliant with ISO/TS 16949 requirements. Buyers acknowledge and agree that, if they use any non-designated products in automotive applications, TI will not be responsible for any failure to meet such requirements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

### Products

|                        |  |
|------------------------|--|
| Audio                  | <a href="http://www.ti.com/audio">www.ti.com/audio</a>                               |
| Amplifiers             | <a href="http://amplifier.ti.com">amplifier.ti.com</a>                               |
| Data Converters        | <a href="http://dataconverter.ti.com">dataconverter.ti.com</a>                       |
| DLP® Products          | <a href="http://www.dlp.com">www.dlp.com</a>   |
| DSP                    | <a href="http://dsp.ti.com">dsp.ti.com</a>   |
| Clocks and Timers      | <a href="http://www.ti.com/clocks">www.ti.com/clocks</a>                             |
| Interface              | <a href="http://interface.ti.com">interface.ti.com</a>                               |
| Logic                  | <a href="http://logic.ti.com">logic.ti.com</a>                                       |
| Power Mgmt             | <a href="http://power.ti.com">power.ti.com</a>                                       |
| Microcontrollers       | <a href="http://microcontroller.ti.com">microcontroller.ti.com</a>                   |
| RFID                   | <a href="http://www.ti-rfid.com">www.ti-rfid.com</a>                                 |
| OMAP Mobile Processors | <a href="http://www.ti.com/omap">www.ti.com/omap</a>                                 |
| Wireless Connectivity  | <a href="http://www.ti.com/wirelessconnectivity">www.ti.com/wirelessconnectivity</a> |

### Applications

|                               |  |
|-------------------------------|--|
| Automotive and Transportation | <a href="http://www.ti.com/automotive">www.ti.com/automotive</a>                         |
| Communications and Telecom    | <a href="http://www.ti.com/communications">www.ti.com/communications</a>                 |
| Computers and Peripherals     | <a href="http://www.ti.com/computers">www.ti.com/computers</a>                           |
| Consumer Electronics          | <a href="http://www.ti.com/consumer-apps">www.ti.com/consumer-apps</a>                   |
| Energy and Lighting           | <a href="http://www.ti.com/energy">www.ti.com/energy</a>                                 |
| Industrial                    | <a href="http://www.ti.com/industrial">www.ti.com/industrial</a>                         |
| Medical                       | <a href="http://www.ti.com/medical">www.ti.com/medical</a>                               |
| Security                      | <a href="http://www.ti.com/security">www.ti.com/security</a>                             |
| Space, Avionics and Defense   | <a href="http://www.ti.com/space-avionics-defense">www.ti.com/space-avionics-defense</a> |
| Video and Imaging             | <a href="http://www.ti.com/video">www.ti.com/video</a>                                   |

TI E2E Community Home Page

[e2e.ti.com](http://e2e.ti.com)

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265  
Copyright © 2012, Texas Instruments Incorporated